ARCAM

ST25



Streamer

The ST25 is an all-new digital audio player expertly crafted in Cambridge, UK.

Exquisite sound quality has been achieved through thoughtful engineering of a new 6-layer digital audio and streaming platform which includes a ground plane through the entire board to keep noise and interference away from the sensitive audio components. These components include the latest Hyperstream iV DAC topology from ESS, in a balanced configuration with advanced Jitter elimination. Sound quality is enhanced further with a new linear toroidal transformer power supply design that drives the entirety of the internal operation with lower noise, and a switching supply that only operates for peak efficiency when in standby.

Up front, the ST25 features a new, bonded 6.5" high-resolution display to show album artwork and metadata which is clearly legible. For playback, an inclusive feature set supports Android and Apple devices, as well as popular streaming services. Connecting the ST25 to your home network with Wi-Fi is quick and straightforward with our ARCAM Radia App. Once connected, enjoy instant playback using Apple Airplay, Google Cast, Spotify Connect, Tidal Connect, and Roon.

The ARCAM ST25 is the ultimate high resolution audio upgrade for any Hi-Fi system, especially the ARCAM Radia A25. Sonically, this combination offers pure audio paradise, thanks to the benefits of isolated components with individual power supplies.

Features

- All new, ultra High-Resolution Streaming Platform to deliver on sound quality and user experience
- New Linear power supply design to deliver peak sound performance
- High-resolution display for clearly visible album artwork and metadata
- Perfect match for the ARCAM A25 integrated amplifier
- Supports Apple Airplay, Google Cast, Spotify Connect and Tidal Connect
- Setup with ARCAM Radia App for presets, Internet Radio and Podcasts
- Supports up to 32 bit / 384 kHz Hires audio
- Roon Ready (after launch)
- Plastic free packaging

www.arcam.co.uk

ARCAM



Services	
Works with (apps)	ARCAM Radia Spotify Connect Tidal Connect Roon
Works with (services)	Apple Airplay Google Cast
ARCAM Radia supported services (Global)	Internet Radio Podcasts UPnP USB Media (using USB-A mass storage input)
Audio Section	
Supported media:	FLAC, WAV (LPCM), AAC, ALAC, AIFF, DSD (up to 256), MP3, OGG, WMA
Supported Bit depth:	16, 24, 32
Supported sample rates (kHz):	Up to 384 kHz
Gapless Playback:	Yes
Digital Audio Outputs	1x Coaxial (RCA), 1x Optical (Toslink)
Analogue Audio Outputs	1x Stereo (RCA) pair
Wireless Specification	
Wi-Fi Network	IEEE 802.11 a/b/g/n/ac/ax (2.4GHz/5GHz)
2.4G Wi-Fi Transmitter Frequency Range and Power	2400-2483.5 MHz (USA 11 Channels, Europe and Others 13 Channels): <20dBm
5G Wi-Fi Transmitter Frequency Range and Power	5150-5250 MHz <23dBm 5250-5350 MHz <20dBm 5470-5725 MHz <20dBm (Not used in China) 5725-5850 MHz <14dBm for EU, <33dBm for other regions.
BLE Transmitter Frequency Range and Power	2400-2483.5 MHz, <10dBm
General	
Mains voltage	100-120V/220-240V 50/60Hz
Power consumption	15W
Power consumption (Network standby)	<2W
Power consumption (Eco standby)	<0.5W
Dimensions W x D (including speaker terminals) x H (including feet)	432 x 329 x 99mm
Weight (net)	5 kg
Weight (packed)	7 kg
Supplied accessories	Mains lead(s) Remote control with 2 x AAA batteries Control Cable Quick Start Guide Important Safety Instructions

